

## How to Set Up the LPR Triggered Recording on a Uniview NVR?



# How to Set Up the LPR Triggered Recording on a Uniview NVR?

#### Description

**Note:** This method is applicable to most of the scenarios, if the method still cannot solve your problem, it is recommended to consult our Tech Support Team. https://global.uniview.com/Support/Service\_Hotline/

### **Operating Steps**

**Step 1** Add the LPR camera to the NVR and register it into the NVR's Video & Image Database server correctly.

**Note:** Make sure the LPR channel number (under setup>camera) and camera ID number (under Platform>Configure VIID Local) are consistent. If the LPR camera is added to Channel 1 on the page where to add the LPR camera as a normal camera, then make sure it is also added to Channel 1 on the NVR Video & Image Database page.

lient	¥	Cam	era		Fisheye	Adv	anced						
Fuetam													
system		Auto	o Switch to '	H 265 00	O Off Note: Effect	ve when first conn	ected	The pag	e where to	add the LPR	camera as a normal ca	mera	
amera	<ul> <li>A:</li> </ul>					1. Jan 1. 1		1.5					
Camera		AUG	D SWITCH TO	U-CODE  011	×	NOTE: LITECTIVE WIN	in first connected						
Encoding		Re	fresh	Modify	Delete Add	Auto Search	Search Segment Batch E	dit Pasa					
OSD		0	No.	Camera ID	Address	Port	Remote Camera ID	Protocol	Status	Vendor	Model	Configure	Access
Image			1	D1 (IP Camera	06) 172.1.90.12	80	1	Uniview	8	UNIVIEW	HC121@1C-085-Z	1	Access
Schedule			2	D2 (IP Camera	02) 172.1.90.80	80	2	Uniview	Ð				Access
Motion			3	D3 (IP Camera	03) 172.1.90.11	\$0	1	Uniview		UNIVIEW	IPC675LFW-AX4DUPKC-VG	1	Access
Video Loss													Part and a second
JNV		•	4 Live Vie	D4 (123456 ew 🔳	7) 192.16.0.11 Playback <b>(</b>	80 Setup	a Smart	ONVIF	B				Access
Tampering JIV Client	Ŷ		4 Live Vie lideo&Ir	D4 (123456 ew 🔳 nage Data	7) 192.160.11 Playback Configure	80 Setup VIID Local	l Smart	ONVE	D				Access
Tampering JOV Client System	~ ~	•	4 Live Vir /ideo&Ir	D4 (123456 ew 🔳	7) 192.16.0.11 Playback C	80 Setup VIID Local	1 2) Smart	ONVIF				_	Access
Client System Camera	~ ~ ~		4 Live Vid /ideo&In Local ID	D4 (123456 ew 🔳	7) 19216.011 Playback 4 . Configure	Setup VIID Local	1 J. Smart	ONVIF	D			-	Access
Tampaging JIIV Client System Camera Hard Disk	2 2 2 2 2 2 2 2		4 Live Vie /ideo&ln Local ID Local Port	D4 (123456 ew  mage Data [ t	7) 192.16.0.1 Playback Configure 0000000001 2000000 5073	80 Setup VIID Local	1 J. Smart	ONVE	BI NV	R Video&Imi	age Database page		Access
Limetion Line Client System Camera Hard Disk Alarm			4 Live Vi fideo&In Local ID Local Port Refresh	D4 (123456 ew anage Data t [	7) 192.16.0.1 Playback Configure 00000000012000000 5073	Setup VIID Local	1 J. Smart	ONVE	B NV	R Video&Ima	age Database page		Access
Client System Camera Hard Disk Alarm Alert	> > > > > > > > > > > > > > > > > > >		4 Live Vi /ideo&lin Local ID Local Port Refresh Car	D4 (123456 ew age Data t [	7) 19216.011 Playback Configure 00000000012000000 5073	Setup VIID Local	1 J. Smart	ONVE	BR NV	R Video&Ima Status	age Database page Advanced		Access
Client System Camera Hard Disk Alarm Alert Network	2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2		4 Live Vi (ideo&In Local ID Local Port Refresh Car	D4 (123456 ew mage Data t ft mera ID	7) 19216.011 Playback C Configure 0000000012000000 5073 C	Setup VIID Local annel ID	J. Smart	ONVF	NV	R Video&Ima Status Dalian	age Database page		Access
Tumpaina Tumpaina Cilient Camera Aard Disk Alarm Alart Vietwork Platform	• • • • • • • • • • • • • • • • • • •		4 Live Vi Local ID Local Port Refresh	D4 (123456 ew E mage Data t t mera ID D1	7) 19216.010 Playback C Configure 0000000001200000 5073 C 140200000	Setup VIID Local II annel ID 21190000011	1 J. Smart	ONVF	IR NV	R Video&Imi Status Online	age Database page		Access
Turnaina JIIV :lient :amera tard Disk Uarm Ulart !etwork !atform ! Video&Image			4 Live Vi Local ID Local Port Refresh	D4 (123456 ew III mage Data ( t t merre ID D1 D2	7) 19216.010 Playback C Configure 00000000012000000 5073 C 340200000	VIID Local  annel ID  VIIS0000011	Smart     Smart     I	OIWF wice Type Nate Recognitic V	NV 2	R Video&Imi Status Online Offline	age Database page		Access
Turnainn JIIV Sljetem Saystem Sawera Hard Disk Alarm Alert Vetwork Platform * Video&Image	v v v v v v Database		4 Live Vi /ideo&In Local ID Local Port Retresh Car	D4 (123456 ew all anage Data t [] mere ID D1 D2 D3	7) 19216.010 Playback Configure 00000000012000000 5073 CONFIGURE 19216.010 CONFIGURE 19407 CONFIGURE 1940	S0 Setup VIID Local II annel ID D1190000011	Smart      Smart      License F      License F      License F      License F	OIWF vvice Type Nate Recognitic '	NV	R Video&Imi Status Online Offline Offline	age Database page		Access

**Step 2** Add license plates from the NVR's web interface under **Smart> Vehicle Control>Plate List**.

*Note:* If there is no specific allowlist or blocklist you wish to use, you can just set a random number.



	Title		How to Set Up the L	PR Triggered Recording on a Uniview NVR?	Version:	V1.1
	Product			NVR	Date	9/26/2023
un	V	🖷 Liv	e View 💷 Playback 🏟 :	Setup & Smart		admin Logout P
3	Plate List 3 Refresh Add	Monito	Refresh Add Delete	Delete All Batch Import Batch Export Export Template		
N=	DefaultList		D No. 4	Plate No.	Modify	Delete
$\odot$			1	123456		丗
Ø						
8	2					

#### Step 3 Set up the LPR monitoring task.

Follow the instructions in the picture below to create the monitoring task and set up the monitoring schedule.



**Step 4** Follow the instructions in the picture below to set **Recording** as **Trigger Action**.

When you set the trigger action under **Match Trigger Action**, then the recording can only be triggered if the captured license plate matches to the plate numbers in the Monitoring List you set.



If you set it under **Not Match Trigger Action**, then the recording is triggered when the captured license plate does NOT match to the plate numbers in the Monitoring List you set.

UN	V	🛡 Live View	📰 Playback 🌣 Se	tup 🎝 Smart	-			a	dmin Logout
6	Plate List	Monitoring							
(A=)	Add Monitoring Task	Delete Task Name	Add Monitoring Task						Monitoring
Ø			Task Name test Monitoring@On OOff Cause of Mtest						
₽ ₽			Monitoring DefaultList Monitoring D1	0					
			Arming Schedule Mate	Trigger Action Not Match Trigger	Action	Goto Preset	D1 V		
			Buzzer Send Email	□ A->1 □ D1->1	D1	∧ Preset	v		
					D3				
					D5				
					D7				
						·			
					ОК	Cancel			_

**Step 5** Set **Normal Recording** schedule or **Event Recording** schedule for the LPR camera. (Normal Recording Schedule is recommended)

unv		📲 Live V	View		Pla	yback	•	s s	otup		J.	Smart				
Client	~	Recordi	ing Scl	hedul	e	Sna	pshot	Schee	dule							
System	~		-	-	-											
Camera		Select C	amera		D1 ()	IP Came	ra 06)	_	_	•						
Camera		Pre-Rec	cord(sec)	)	10	1				~						
Encoding		Post-Re	cord(sec	<)	60					Y						
OSD		Redund	iant Reco	ording	Q.Pr	n e of	Note	: Please	set at l	least on	e redun	idant dis	k.			
mage		Recordi	ing Sche	dule	) Or	n O Of	f									
Schedule		-	2		1											
Motion Video Lorr		Ed	it		+											
Tampering		Mon	0	2	4	6	8	10	12	14	16	18	20	22	24	South-
Privacy Mask		Tue													2	Normal
Snapshot		Wed													3	Event
Audio Detection		Thu													4	Motion
Human Body Dete	ction	Fri													5	M and A
Hard Disk	.w.	Sat	-												9	M or A
Alarm		Holida													8	None
Alert	Ψ.		0	2	4	6	8	10	12	14	16	18	20	22	24	
Network	~			1												
Platform	¥	Copy to	IAI	-									v			
User	V	Save														
Maintenance	~															
Backup	~															

Now you should be able to search and find the LPR triggered recording clips from the NVR's monitor when the LPR captures license plates.



Ti	tle		How to Set Up th	Version:	V1.1		
Pro	duct			Date	9/26/2023		
				VCA			
Ē	VCA Conf		cle Search				
Camera			Select Camera	All			
	Analyzer	Con	Start Time	2022-04-01 00:00:00			
$\bigcirc$	List Mana		End Time	2022-06-29 23:59:59			
VCA			Filter By	All			
	Vehicle C		Plate No.				
	VCA Sear	ch V	Vehicle Color	All			
Network			Plate Color	All			
System	Face Com Vehicle Si Behavior	earch Sea			×		
	People Co						
	Heat Map						
Alarm							
vaintain			Search E				

