

How to Access a Uniview Device's Web Interface through EZCloud Account?



How to Access a Uniview Device's Web Interface through EZCloud Account?

Description

Note: This method is applicable to most of the scenarios. If the method still cannot solve your problem, it is recommended to consult our Tech Support Team. <u>https://global.uniview.com/Support/Service_Hotline/</u>

Operating Steps

You can access the web interface from EZCloud website or EZStation.

From EZCloud Website:

Step 1 Please visit the EZCloud website and log in your EZCloud/EZView account.

Account registered to countries in **North America** and **Latin America**: <u>https://os.ezcloud.uniview.com/</u>

Account registered to countries in **Europe** and **Africa**.

https://eu.ezcloud.uniview.com/

Account registered to countries in Asia and Oceania

https://ap.ezcloud.uniview.com/

	Username/Email Mobile Phone Number	
	L Username/Email	
	Username/Email is required.	
	Password	
	Password is required. Forgot Password?	
~	Login	
ĽĊ	Don't have an account? Sign Up	
	and the second sec	



through EZCloud Account? Version: V1.1 Date 9/26/2023

Step 2 Download the P2P plugin and install it.

EZCloud	g-In. Versions before 1,16,0001 will not be	supported. To view your current plugie v	ersion, click Control Pariet > Programs and	Features > EZCloud_P2P. Please close your brows Wetcome unv_ue Legout Download AP	er before installation and ignore anti-vin IP Help 🔻 Uniview Official Website
Device Management	Organization Management	Sharing Records	Personal Info		
rganization	My Cloud Devices Devices	s Shared to Me			
Piease enter organization name	+ Add 💼 Defete (3 Refresh		Online Device 2 Total Number 7	Please enter device name Q
e 🚠 root	IP Address	Device Name	Model Organizat	ion Latest Online Time Status	s Operation

Step 3 Find the device you wish to access from My Cloud Devices or Devices Shared

to Me under Device Management. Click e under the Operation column to access the web interface of this device.

a ball & Street &	all residence and shall a	1 (10) 1 (10) 1 (1)	A REAL PROPERTY AND ADDRESS.				-
	Passe did	Countrary for the latest PDP service prop-	in Versions Below 1.10.0001 will not be supported. To view part surrent p	aligie retries, plot Doebst Panel - Program and Federer - 020064	739 Paase sloss participants taken includer and gr	nen anti-aca darb	
EZCloud					Status	ning of Light (Downed MP (two *)	Univer Official Vietorie
Device Management	Organization Management	Sharing Records	Personal Info				
1	1						
Cellinitation	My Child (Helder David	an travel to Ma					
	+ Abd 📋 Delate	() Reback				Online Device 2 Notal Number	Please inter device taxes
Plass ette oprivalen nameQ			Devre News	Mindel	Organization	Labor Onion Tama 121	to Contener
Mass arbs représententiere Q	0	IT A SCHOOL					
Place of the approximation of	0	72.114.201.13	WR mur	XMIDI2 MQ3	int	09542925-15.21134	

From EZStation:

Step 1 Log in your EZStation and the cloud account under **Device Management**>**Cloud Device.**

EZStation	1 Device Management
Device Group	
Encoding Device Decoding Device	Login Register
Access Control Device	Cloud Login X
Metwork Keyboard	Username unv_us Password ••••••••• Auto Login Apply for a new account Forgot Password
	Login



Step 2 Go to **Device Details** to add the devices to manage if it has not been added before.

EZStation	l Device Management	
Device Group		↓
📻 Encoding Device	Cloud Account: unv_us Refresh My Cloud Device(Added 4)	Switch Account Device Details Exit
💼 Cloud Device	Cloud Name Loca	l Name Model
📻 Access Control Device	ptz tracking issue ptz t	NVR301-08LE-P8 racking issue NVR302-0852-P8

Step 3 Go back to **Cloud Device** and find the device you wish to access the web interface of. Click ^(e) under the Operation column.

